

TABLE OF CONTENTS


OVERVIEW	3
PACKAGE CONTENTS	3
FEATURES	4
GEMINI 4:4:4 ANATOMY	6
MENU STRUCTURE	7
GEMINI	8
INPUTS	9
RECORD	9
OUTPUT	10
MENU QUICK KEYS	10
PREPARATIONS.....	12
TIPS, TECHNIQUES & RECOMMENDATIONS	12
POWER	14
AC Power Supply	14
Camera	14
REGISTRATION	15
SETTING DATE & TIME	15
SETTING METADATA	15
DPX HEADER METADATA	16
XML FILE	16
HANDLING SSD CARDS	16
FORMATTING SSD CARDS	16
SSD Status Indicators	17
System Status Indicators	17
RECORDING	18
Recording Time / Media	18

Recording Instructions	18
DPX	19
PLAYBACK	20
PLAYLIST	20
TRANSFER	22
Best User Practices	22
Performance	22
File Support	22
Transfer Configurations	24
Accessing & Using the SSD on A Computer	25
POST WORKFLOW	27
APPENDIX	31
Firmware Updates	31
Specifications	35
Gemini Mechanical Drawings	36
Remote Connector Pinout	36
Firmware Version 1.0.592 (see also Release Notes)	37
Features	37
Known Issues - 1.0.594	39
Trouble Shooting & Support	40
Limited Warranty	41
Obtaining an RMA	42

OVERVIEW

PACKAGE CONTENTS

Make sure you have the following items, supplied with your Gemini 4:4:4 upon purchase.



Hard Case



Gemini 4:4:4



Transfer Station



HDMI
Type C to Type A



HD-SDI (Qty 2)



eSATA
Data Cable



Power D-Tap
4-Pin



USB Mini Type A
(transfer station power)



XLR Power Cable
4-Pin



Universal AC Power
Supply



Stylus &
Microfiber Cloth



Hot Shoe Mount

NOTE: Only Convergent Design SSD's will work in the Gemini 4:4:4. These SSD's, available in 256GB and 512GB, must be purchased separately. Your Gemini 4:4:4 [dealer](#) is an ideal place to purchase these SSD's.

FEATURES

The Gemini 4:4:4 is a professional, high-definition video recorder that fits in the palm of your hand and is easily mountable on your camera. It is very light weight and small in size.

Gemini 4:4:4 functions as a high-quality monitor, with a wide viewing angle, high brightness with great contrast, and no compromise video playback device.

The footage from the Gemini 4:4:4 can be easily incorporated into virtually any workflow using your favorite codec or as native uncompressed DPX sequences.

With an extra cost option, Gemini 4:4:4 is also capable of recording, combining, and playing back 3D video.

The Gemini 4:4:4 records to specially certified and tested 1.8" solid-state hard drives that can be purchased from Convergent Design through your local dealer.

UNCOMPRESSED 4:4:4 RGB QUALITY

The Gemini 4:4:4 records in the highest quality possible; no other recorder exceeds the image quality of the Gemini 4:4:4!

The Gemini 4:4:4 records Full Uncompressed 4:4:4 RGB and also accepts 4:2:2 camera signals. This ensures that 100% of the quality of your video signal will be maintained. There are no signal losses, no artifacts, and no loss of quality whatsoever.

This is especially important when recording Log video, such as Sony S-Log or Log-C. The precise values for each bit are recorded. No bit values are changed in any way, thus preserving the full integrity of your images. Recording full 4:4:4 is the proper way to record S-Log and Log-C. Recording 4:2:2 from a 4:4:4 capable camera is a compromise.

4:2:2 to 4:4:4 UP-CONVERSION

The Gemini 4:4:4 records in DPX file format, an industry standard for high end post processing. To conform with widely used software that accepts the DPX file format, the Gemini 4:4:4 automatically up-converts (up-reses) to 4:4:4.

This is accomplished by using a sophisticated routine that uses the weighted average of nearby pixels to ensure that the 4:4:4 is of high quality, even when the source video is 4:2:2.

HD TOUCH SCREEN FOR RECORD AND PLAYBACK

The Gemini 4:4:4 is easily controlled using the touch screen. A Stylus is provided to prevent the LCD Monitor from being smudged.

NOTE: Your camera MUST be equipped to output 4:4:4 in order to use the uncompressed 4:4:4 functionality of the Gemini. A 4:2:2 signal will be up-resed to 4:4:4.

DUAL SSD

The Gemini 4:4:4 is unique in that it supports two SSD's for both recording and playback.

To extend recording time, a recording can automatically span from one SSD to another. This is fully automatic.

S-LOG and LOG-C SUPPORT

Many features are built into the Gemini 4:4:4 for supporting Log footage: A menu option easily allows one to apply a built-in LUT (Lookup Table) to native S-Log footage. The LUT is applied to the LCD and HD-SDI outputs.

LOG RECORDING

The Gemini 4:4:4 is ideally suited for recording Sony S-Log and also supports Log-C.

DUAL LINK SDI

The Gemini supports dual link 1.5Ghz HD-SDI Input for 4:4:4 recording.


HIGH PERFORMANCE SSD'S

The Gemini 4:4:4 SSD's are specially picked for their performance and reliability. These SSD's are capable of reading at greater than 400Mbps, making transfer of files very quick. You'll find these [Convergent Design SSD's](#) available through our [Dealers](#) at affordable rates.

FAST BOOT TIME

You can expect your Gemini 4:4:4 to power up and be ready for recording in approximately 12 seconds or less after applying power.

GEMINI 4:4:4 ANATOMY






WARNING: DO NOT ENCLOSE THE UNIT IN AN AIRTIGHT CONTAINER
 Keep the area around the cooling fins (vertical lines on the back of the Gemini) open for air flow. Gemini 4:4:4 and SSD's will operate at full potential under these conditions. Keep the unit vertical for best cooling.

MENU STRUCTURE

The Gemini 4:4:4 menu can be accessed through the buttons along the top of the screen. By tapping on a Main Menu heading, a Sub-Menu 1 navigation will appear. Likewise, by tapping a Sub-Menu 1 heading, a Sub-Item 2, and so on, may appear and subsequently provide you with an Option related to that.



GEMINI

Sub-Menu 1	Sub-Menu 2	Sub-Menu 3	Option	Description	Additional Information
SET	LCD	Auto-Hide	On	The on screen menu will disappear after 15 seconds of idling. Touching the screen anywhere will bring the menu back.	
			Off	The on-screen menu will always be displayed unless the hide button is touched.	
		Guides	2.39:1		
			1.85:1		
			None	Removes any current Guides setting.	
		Flip	On	Flip the video and on-screen display by 180°.	Great for certain mounting options. Note: THIS DOES NOT FLIP THE RECORDED IMAGE!
			Off	Flip the video and on-screen display to normal view.	
		Brightness	→	Adjustable in 10% increments. Click OK to save selection.	
	Time	→	→	Set the appropriate time.	
	Date	→	→	Set the appropriate date.	
	Reset	→	→	Restore all default settings.	
	Keys	Unit	OK	Indicates your product was successfully registered.	Requires nothing further after initial registration.
ABOUT	→	→	→	Displays the firmware version, serial number of your Gemini unit, and warranty date.	
SSD's	Format SSD 1	→	→	Permanently erases everything on SSD 1.	WARNING: DATA WILL NOT BE RECOVERABLE!
	Format SSD 2	→	→	Permanently erases everything on SSD 2.	

INPUTS

Sub-Menu 1	Sub-Menu 2	Sub-Menu 3	Option	Description	Additional Information
TIMECODE	Source	→	SDI	Timecode is extracted from the SDI signal coming from your camera.	For non-zero timecode, set your camera's timecode output (if it has one).
			LTC	LTC to 6 pin via remote port and adaptor cable.	
AUDIO	Channels	→	2		


RECORD

Dropdown	Sub-Item	Sub-Menu 3	Option	Description	Additional Information
TRIGGER	Rec Button	→	→	Recording is started by touching the record button on the Gemini screen.	
	SDI Timecode	→	→	Recording will start when incrementing timecode is detected from the SDI input and will stop recording when timecode is not incrementing.	This mode is particularly useful when wanting to trigger a record session from your camera's record. However, your camera will most likely output incrementing timecode while it is playing back video. This will also trigger a record in the Gemini. Therefore, this setting may need to be turned off while your camera is in playback mode
CLIP	(Clip Name)(Clip #) (AAAAAAA)(000)	→	→	Allows the user to set the name of the recorded files.	The last three digits will auto-increment from one recording to the next. If you are using more than one Gemini unit, it is recommended that at least the first two characters of this name be set different from one Gemini unit to the next.

OUTPUT

Sub-Menu	Sub-Menu 2	Sub-Menu 3	Option	Description	Additional Information
REC TALLY	On	→	→	When the Gemini is recording, the SDI and HDMI output will display a red bar on the bottom of the screen to indicate an active record.	This red bar is not recorded in the Gemini. If you are using a separate recorder to record the output of the Gemini, turn this setting off.
	Off	→	→	Nothing will be overlaid on the SDI or HDMI output of the Gemini.	
MODE	4:2:2	→	→	SDI output as 4:2:2; works in both Rec and Play Mode.	This setting only affects the output video. 4:2:2 Input will always be converted to 4:4:4 for recording.
	4:4:4	→	→	Incoming video will be output as 4:4:4.	Use this setting if you want to output 4:4:4 RGB, usually Dual Link HD-SDI. (Not valid with 4:2:2 input)

MENU QUICK KEYS



Menu

Click to reveal main menu structure. Click << to collapse.

Hide

Click to remove all content/buttons from the screen. Tap the monitor anywhere to reveal

Metadata (Rec Mode) / Playlist (Play Mode)

See [Preparations: Setting Metadata](#) page 12 for more information on Metatdata.


See [Playback](#) page 19 for more information on Playlist.

Next Take

Click to reveal Clip, Scene and Take info. Click << to collapse.

MODE TOGGLE & STATUS

Across the bottom of your Gemini monitor you will find the Control Bar, including Mode Functions and related Indicators and Buttons.



	Description				
Status Line	The status line will indicate when you have successfully changed or applied a setting.				
Record / Play / Stop Button	Click to initiate the appropriate action. Record Stop Play Pause				
Scene & Take	Scene name set in Metadata; Take auto-increments from one record to the next. SCENE----- 001				
Timecode	12:25:22:22				
Mode Switch	Tapping will move the arrow (“>”) to toggle between Rec and Play Mode. > REC PLAY				
Remaining Record Time	Remaining record time per card, shown as SSD1 / SSD2.				
Quick Key	Click the caret  to display options, then click to apply. <table> <tr> <td>Apply LUT</td><td>NOTE: Viewing LUTs are not applied to recorded material (4:4:4 input only).</td></tr> <tr> <td>1:1 Pixel</td><td>For critical focus.</td></tr> </table>	Apply LUT	NOTE: Viewing LUTs are not applied to recorded material (4:4:4 input only).	1:1 Pixel	For critical focus.
Apply LUT	NOTE: Viewing LUTs are not applied to recorded material (4:4:4 input only).				
1:1 Pixel	For critical focus.				

PREPARATIONS

TIPS, TECHNIQUES & RECOMMENDATIONS

The Gemini 4:4:4 is a sophisticated, technologically advanced device. A few simple tips, techniques and recommendations can help ensure a successful shoot.

1. Register your unit now, as you need access to the Internet to do so.

It must be registered. Otherwise the unit is disabled.

2. Obtain the Gemini 4:4:4 and all the necessary batteries, chargers well in advance of your shoot. Please be certain to plug the power cable into the power input, which is on the left side, the remote control connector is on the right side. Forcing the power connector into the remote control connector will damage the Gemini 4:4:4.
3. Obtain genuine Convergent Design SSD's. No other SSD's will work in the Gemini 4:4:4. This is to ensure that the SSD's are fast enough and have been fully tested prior to your shoot.
4. Extra, high quality HD-SDI cables are very desirable and should be available on every shoot. These must be good quality 75 Ohm cables with true 75 Ohm connectors.
5. Please read the manual, you will gain a lot of practical knowledge.
The latest version is on our website:
<http://convergent-design.com/LinkClick.aspx?fileticket=CdmSeL04O18%3d&tabid=139>
6. We generally recommend that you use the latest firmware.
<http://convergent-design.com/FirmwareUpdates/Gemini444.aspx>
7. Test the unit and the SSD's, with your camera, in advance of the shoot.
Setup your camera, exactly as you will for the shoot, setup the Gemini 4:4:4, create some test footage, and run this test footage through your Post workflow. Ensure that your Post department can handle the full uncompressed workflow. Full uncompressed video is great, it is just different. Many systems support DPX, but not all.
8. For editing DPX Files using Final Cut Pro, please obtain GlueTools.
<http://gluetools.com/products.html> Select "Cineon/DPX Pro for Final Cut Studio".
9. Obtain a way to back up your data in the field. A good backup procedure is to have two backups, stored on separate devices, and have all of your footage checked visually, prior to reformatting and reusing the SSD's.
10. Purchase enough SSD's, plus some extras. Be certain that you have enough so that you can shoot while the backups are being made and the footage is being checked.
11. While shooting, during breaks, playback you footage, from within the Gemini 4:4:4 to check that everything is working fine. But, more importantly, transfer you footage to a backup, then play the footage from the backup to ensure that all is good!
12. Call for support whenever you wish. We strive to provide world class support 24/7.
If you don't reach us at one number, try another.

Support Contact Info: See Page 40.

13. Ensure that camera viewfinder data is not being sent to the Gemini 4:4:4.
Record a test, and then play it back. If you see viewfinder data while you are recording, or on playback, there is a major problem and your camera settings must be changed.
14. Do not use Beta firmware for production work!
15. Do not over-tighten the ¼" x 20 or 3/8" x 16 screws. You can damage the case.
16. Please do not open the Gemini 4:4:4 case, as this voids the warranty.
17. Here is a tip to help your shoot be a success:
The most successful teams plan ahead, and check out all of their gear in advance.
18. Never format an SSD unless you are certain that the footage has been transferred, and checked.
To be safe, wait until you have the footage in two places.
19. Never attempt to write files to the SSD, nor delete files off the SSD and then reuse the SSD in the Gemini 4:4:4.
20. It is acceptable to upload files from an SSD, using our Transfer Station, then reinsert the same SSD into the Gemini 4:4:4 so that you can continue shooting.
But, as noted above, do not delete files off the SSD, then attempt to shoot more.
21. Always format the SSD's, in the Gemini 4:4:4.
Formatting an SSD in another device is not acceptable.
22. Never put the Gemini 4:4:4 in a confined enclosure, it needs access to fresh air for cooling.
23. Never leave the Gemini 4:4:4 in hot sun without protection for an extended period of time. If it has been in a hot car, please allow time for it to cool.
24. Protect it from rain, splashes and other inclement weather.
25. Do not leave the Gemini 4:4:4 flat on a table with the power on.
A vertical position is best as it allows air to flow naturally over the cooling fins.
26. Do not feed the Gemini 4:4:4 reverse-voltage DC, or voltages over 19 Volts.
Do not plug in the Anton Bauer D-Tap or P-Tap connectors in backwards.
Caution: Some non-Anton Bauer P-Tap power outlets allow the P-Tap or D-Tap connector to be plugged in backwards.
If you do, then the Gemini 4:4:4 will stop working and it will have to be repaired.
27. Respect the Touch Sensitive LCD. Do not use hard objects to operate the touch screen.
A ball point or other pen should not be used. Use our provided stylus or something similar. Caution: The Touch Screen and LCD are expensive to replace.

POWER

There are multiple ways to power your Gemini 4:4:4;

1. Using the provided AC Power Supply which includes international power plugs
2. Using 4-Pin XLR Power, using the supplied 4-Pin XLR to 4-Pin Hirose Power Cable.
3. Using an Anton Bauer or IDX Battery with a D-Tap connection. A D-Tap to 4-Pin Hirose Power Cable is included.
4. Using any 4-Pin Hirose Power cable as provided by Convergent Design for Gemini 4:4:4 or nanoFlash.
5. Using any suitable DC power source, 6 to 19 Volts DC, with a 4-Pin Hirose connector.

Pin 1 & 2 Must be Positive DC Voltage

Pin 3 & 4 Must be Negative or Ground

Power Supply must supply at least 15W.

WARNING! Power input is limited to 6-19 Volt DC.

AC Power Supply

Simply connect the 4-pin Hirose to 4-Pin Male XLR cable to the Female 4-Pin XLR connector on the AC Power Supply and plug into a suitable AC power source.

Gently turn to fit and click the Hirose connector into the Power 6-19V connector on the left of the Gemini 4:4:4.

Do not force the power connector into the Remote Tally connector on the right side of the Gemini 4:4:4.



Camera

Using the supplied HD-SDI cables, or other high quality True 75 Ohm HD-SDI cables with True 75 Ohm connectors, connect your camera to SDI A, or to both SDI A and SDI B (for Dual Link).

Use of 50 Ohm and/or low quality cables will cause the video signal to be intermittent.

REGISTRATION

If you haven't already, you will need to register your Gemini 4:4:4 at www.Gemini444.com to activate your unit.

Your information is private and used internally to send you firmware updates via email. We highly encourage you to enter the optional information that we request. This extra information is designed to help us provide product improvements as well as better products for you.

When you power up the Gemini for the first time, it will automatically provide you with a serial number that you will need for your on-line registration, via the website.

PLEASE REGISTER YOUR UNIT AND
OBTAIN UNIT ACTIVATION KEY AT:
HTTP://GEMINI444.COM
OK
SERIAL = 10110123123

- (1) Tap the OK button when you are ready to proceed.
- (2) Enter Unit Activation Key using the + and - buttons; Press OK.
- (3) Activation is complete if you have received the 'Unit Activation Successful' in the Status Line.

SETTING DATE & TIME

The Gemini | Set | Time and Gemini | Set | Date menu items are used to set the internal clock of the Gemini 4:4:4, which keeps time even when there is no external power connected to the unit.

SETTING METADATA

When Gemini 4:4:4 is in Rec Mode, you can edit Metadata.


Tap the 'Metadata' Menu Quick Key to reveal the following editable data: Reel, Scene, Take, Day, Camera, and Project.

This information is stored until changed or power is removed.

Some of the metadata is displayed for each clip in Play Mode, including: Scene, Take, Timecode, Date, Time and Shooting Day.

REEL : ----
SCENE : -----
TAKE : 000
DAY : 000
CAMERA : -
PROJECT : -----

To edit, simply tap the field you would like to edit, then tap the character field to reveal a character toggle. You may edit multiple fields before choosing OK to save your changes, or X to revert to previous.



DPX HEADER METADATA

During record, metadata is saved in various locations within the header of every DPX file. This data is viewable in some software on a computer. Additionally, the metadata is stored in a separate XML file alongside the DPX files for a given record.

File Field	Values for Data Input Included
DPX Slate Info	Reel, Scene, Take, Day
Input Device Name	Reel
Input Device Serial Number	Camera
Project	Project

XML FILE

All metadata fields and additional clip information are stored for each recording.

HANDLING SSD CARDS - [READ THE FULL SAFE HANDLING DOCUMENT](#)

Avoid touching the connector end of the SSD's.

Avoid shocking the connector end of the SSD's via static electricity.

When inserting into the Gemini 4:4:4, make sure the label is facing the front of the unit (see the proper placement in the image below).

Please be gentle when inserting the card. Clamping the door over the card and gently pushing in the drawer will adequately connect the drive.



FORMATTING SSD CARDS



WARNING: BEFORE USING THE SSD'S IT IS IMPERATIVE TO FORMAT THE SSD'S IN THE GEMINI 4:4:4

ALL EXISTING DATA WILL BE LOST DURING THE FORMAT!

Formatting is a destructive process. Any data on your SSD's that has not already been transferred to another medium will be lost forever. Once this


process is started, there is no way to recover the data. “Un-format Utilities” will not be able to recover the data.

Go to **GEMINI > SSD's > FORMAT SSD1** or **GEMINI > SSD's > FORMAT SSD2** from the Menu to format the SSD's.

This process will take approximately 30 seconds for a 256GB and 60 seconds for 512GB cards.



After the SSD's have been used to record any video, the video must be transferred to another device, before reformatting the SSD's, otherwise the video will be lost forever.



SSD Status Indicators

The LED lights associated with each SSD drive will display the following status color indicators:

-  Drive needs to be formatted within the Gemini.
-  Drive is completely full and can be played back or formatted for a new record.
-  Drive is ready to record.
-  SSD card is initializing.
-  Drive is currently playing back.
-  Drive is currently recording. **NEVER REMOVE SSD DURING RECORD OR PLAYBACK!**
-  Powering Up; System Test
-  Drive has old clips which can be played back but to record new SSD's must be formatted.

System Status Indicators

The LED lights located in between each SSD drive, in the middle of the unit, will display the following status color indicators:

-  Ready for record.
-  Recording. **IF FLASHING RED, SEE TROUBLESHOOTING BELOW.**
-  Play Mode. **CURRENTLY PLAYING.**

RECORDING

Recording Time / Media

Media	1080p24 4:4:4	1080p25 4:4:4
256GB SSD (x1)	21	20
256GB SSD (x2)	42	40
512GB SSD (x2)	84	80

Recording Instructions


Are you ready to capture the ultimate quality? The following will walk you through a successful recording.

- (1) Assure you have an appropriate power supply.
- (2) Make sure any and all necessary settings have been programmed and saved.
See Preparations: Setting Metadata page xxx
- (3) Insert at least one Convergent Design SSD card into either Slot 1 or Slot 2, or insert one in each slot. For more information on '[Handling SSD Cards](#)', visit page 14. The LED SSD Drive Indicator light should be green. If so, proceed to step 4.

TROUBLESHOOTING. If the SSD Indicator(s) are NOT green, try the following:

Orange	SSD drive is initializing. If it does not change after 30 seconds (for 256GB)/ 60 seconds (for 512GB), power cycle the unit.
Yellow	Go to GEMINI > SSD'S > FORMAT SSD (1 or 2).
White	Card is full; remove the card and transfer the data.

- (4) If the arrow ">" is next to 'REC' on the Mode Toggle, you are ready to record.
If not, tap the Mode once to toggle to 'REC' mode.
- (5) Make sure the System Status Indicator is green.
- (6) Tap the Record Button to begin your Clip.



- (7) Your clip is now recording. Please note:
- The System Status Indicator is red.
 - One of the SSD Status Indicators is Red. If you have two cards in, the other light should be green.
 - The Status Bar will turn red and your time code should be incrementing.



- (8) To stop recording, click the blue Stop Button. The Status Line will indicate that the “Record is Complete”.
- (9) Record again, or, to watch your clip(s), you are ready for Playback Mode.

DPX

Gemini records video into DPX (.dpx) files. DPX is a file format that is specifically designed for uncompressed video. Each DPX file actually only stores one single frame of video. Therefore, each record will have a single folder that contains all of the DPX files. For NLE workflow options, see **TRANSFER**, page 18.

TIP: Clip Name and Clip Number (AAAAAAA) (OOO) will increment.

This can be adjusted by the User under the RECORD | CLIP.

PLAYBACK


Now that you have successfully recorded to your Gemini 4:4:4, it's time to harness its playback capabilities on its high-definition 800 x 480 monitor.

- (1) If the ">" is next to 'PLAY' on the Mode Toggle, you are ready to play back. If not, tap the Mode once to toggle to **PLAY Mode**. The Status Line will indicate that you are now in Play/Review Mode.



WARNING: DO NOT REMOVE EITHER SSD CARD DURING PLAYBACK.
THIS MAY RESULT IN DATA THAT IS UNRECOVERABLE.

- (2) Tap the blue **Play Button**.
The most recent clip taken will immediately begin playing.




- (3) When **Play** has been initiated, the button will change to a **Pause Button**.
- (4) When you have completed your review, tap the Mode again to toggle back to **REC Mode**.

PLAYLIST

For additional options in playback, you may choose the 'Playlist' Menu Quick Key to display a list of clips, including metadata and other clip information.

To reveal/hide clip info, simply tab the << button.



- (1) Make sure your Toggle is in 'PLAY' Mode.
- (2) Click the Playlist Quick Key in the left, upper-third of the monitor. 
- (3) Select/deselect by tapping the box next to a clip. [X]
 - a. You may choose multiple clips.
 - b. Use the page arrows,  , to reveal additional and previous clips (5 clips displayed per page). Selections from previous page will not be lost when using this function.
 - c. Choose 'ALL' to select all available clips.
 - d. Choose 'LOOP' to loop or continuously play selected clips.
- (4) Tap the Play Button.
 - a. Tap Pause Button to pause.
 - b. Toggle to REC Mode when completed to stop.

TRANSFER

Data from your SSD is copied over eSATA; USB is used for **ONLY** powering the Transfer Station. Data cannot be copied via USB.

If your computer is not equipped with an eSATA port then you will need to purchase an Adaptor, or expansion card. Additional options include USB 3.0 to eSATA Adaptor, or PCI eSATA Adaptor.

Best User Practices

The best way to transfer is to connect the eSATA adapter, the Transfer Station and the SSD, **then** boot the computer.

Use 6 GB eSATA adapters for maximum performance.

Do not force cables or the SSD into Transfer Station.

(See image for proper connectivity)



Performance

The Gemini 4:4:4 SSD's can perform up to 400MBps. Keep in mind you will be limited by the slowest median in the transfer process. For example: eSATA 3Gbps cards have a max performance of ~270MBps, and eSATA 1.5Gbps have a max performance of ~130MBps.

Typical Hard Drives (Non-Raid) generally perform anywhere in the range of 80-130MBps. For maximum performance, make sure you are using eSATA 6 Gbps to a Raid configuration.

Video Format	Video Data Rate Mbytes/Sec
1080p24 4:4:4 10-Bit	186.6
1080p25 4:4:4 10-Bit	194.4
1080p30 4:4:4 8-Bit	186.6
1080p30 4:4:4 10-Bit	233.3

**It's recommended to not exceed 250 clips per card.

File Support


The Gemini 4:4:4 recorder accepts inputs from both HD-SDI 4:2:2 and 4:4:4 cameras. 4:4:4 Cameras currently must have HD-SDI Dual Link. HD-SDI 3G will be supported in a future firmware release.

All DPX files are recorded so that each frame of video is a single file, with all frames from a single recording being contained within a single file folder.

All Files Recorded by the Gemini 4:4:4 are recorded as 4:4:4 10 Bit RGB DPX Files; as this is the industry standard.

T

Thus, each time you start and stop a recording it will create a new file folder, which takes the name of the Clip, as setup via a menu item in the Gemini 4:4:4: All clips reside in a **}CLIPS{** folder on the Solid State Drive (SSD).



}CLIPS{

CLIP0001001 (Assuming that the **RECORD|CLIP** is set to (CLIP001) (001))

CLIP0001001.0000001.DPX

CLIP0001001.0000002.DPX

Etc.

CLIP0001002 (Assuming that the **RECORD|CLIP** is set to (CLIP001) (002))


CLIP0001002.0000001.DPX

CLIP0001002.0000002.DPX

Etc.

DPX Frames May contain up to 60,000 Frames per Clip (Based on 512GB Drive)

Transfer Configurations



Accessing & Using the SSD on A Computer

SSD's used with the Gemini will report as almost entirely full (~250 MB free) on a computer, as the Gemini reserves almost the entire SSD for video only, and prevents the computer from writing to this area. Thus the Gemini video area on the SSD is essentially read-only on a computer).

The SSD's can be used on a computer for playing video directly from the card, for copying video onto the computer's file system, or to copy firmware update files from computer to SSD for updating the Gemini (see the User Manual for more details on updating the Gemini).

Note: Macs require a PCI->Sata Expansion Card to be able to attach a SSD to the Mac via the Transfer Station.

Mac

Insert the SSD (label up) into the provided Transfer Station, and attach the Transfer Station to the Mac via PCI->SATA port and the USB port (which only provides power).

The SSD will appear as a Volume within Finder on the Mac, and can be treated as part of the File System. Like other Volumes on the Mac, the Volume must be dismounted within Finder before being physically removed from the Transfer Station.

PC

For Windows 7 PC's: **Important*: First disable caching of the SSD within Windows, to allow for consistent and correct display of files from 1 SSD insertion/removal to the next.

To disable caching to the SSD:

1. Insert the SSD (label up) into the provided Transfer Station, and attach the Transfer Station to the Pc via the SATA port and the USB port (which provides power).
2. Within Windows Explorer, find the Drive Letter associated with the just inserted SSD (256 or 512 GB SSD with ~250 MB available).
3. Right-click the Drive Letter, in the Drop-down Menu choose "Properties".
4. Choose the "Hardware" tab.
5. In the available list, choose the option which begins "C400" - be sure to choose the "C400" option and not a different drive.
6. Click the "Properties" button.
7. Choose the "Change Settings" button.
8. Click the "Policies" tab.
9. **Turn "off" (un-check) the "Enable write-cache option",** or in some versions of Windows 7, select (check) "Quick Removal" option.
10. Press "Ok" and you're done.

This procedure may need to be repeated if a future insertion of an SSD creates a different Drive Letter within Windows Explorer. If the Drive Letter does not

change from one insertion to the next, the procedure does not need to be repeated.

If you are unable to perform the above, For Windows 7, then you may power your computer off, then attach the Transfer Station, SSD, and both cables, then power on your computer. In this case, the computer should recognize your drive. After copying files to the SSD, you may need to shut down your computer, for the Windows Cache to be cleared (so that the files are actually written to the SSD).

Allow 10-20 seconds for Windows to recognize the SSD, after insertion.

Windows XP:

Avoid having the SSD attached at time of booting a Windows XP machine. Otherwise, if an SSD is attached at time of Windows boot-up, Windows may try to boot from the SSD.

When removing an SSD from the Transfer Station, allow at least 15 seconds before inserting another SSD.

Allow 10-20 seconds for Windows to recognize the SSD, after insertion.


POST WORKFLOW

Adobe



Software	Imp/Exp	File Type	Function and General Notes
After Effects CS4 CS5 CS5.5 	Import	Native Support	• Check Playback • Apply Color Correction • Apply LUT • Can be sent directly to Adobe Premier / Media Encoder
	Export	• After Effects Project • Premier Pro Sequence • Uncompressed Quicktime Movie	
Media Encoder CS5 CS5.5 	Import	• After Effects Project • Premier Pro Sequence	• Encode *This will be dependent of any Codec installed on your machine
	Export	• Uncompressed Quicktime Movie • *Codec of Choice DNxHD, XDCAM, ProRes	
Photoshop CS4 CS5 CS5.5 	Import	Native Support	• Viewer (individual frames) • Used to check a Single Frame
	Export	• DPX • JPG, etc.	
Premier Pro CS4 CS5 CS5.5 	Import	Native Support • After Effects Project • Premier Pro Sequence • Uncompressed Quicktime Movie	• Be sure to select "Numbered Stills" Option... • For optimal playback, import as After Effects Project or import as Premier Pro Project directly from After Effects.
	Export	Final Production	(Deliverable File)

Apple



Color 1.5.3 (FCP7) 	Import	Native Support		• Check Playback • Apply Color Correction • Apply LUT
	Export	Final Cut Pro Project / Sequence		Export to Final Cut Pro
Compressor 3.5(FCP 7) 4 (FCP X) 	Import	Plug In 	• Glue Tools (Mac) • Cineform Remaster	• Encode
	Export	*Codec of Choice: DNxHD, XDCAM, ProRes		*With Glue Tools you can import DPX files, then Encode to Codec of choice
Final Cut Pro 6 7 X 	Import	Plug In 	• Glue Tools (Mac) • Cineform Remaster	• Check Playback • Edit
	Export	Final Production (deliverable file)		*Plug In allows you to import DPX files directly

AutoDesk

Smoke 	Import	Native Support		• Check Playback • Apply Color Correction
Flame 	Export	• NLE • Uncompressed Quicktime Movie • Final Production		• Apply LUT • Edit

Avid

Avid DS 10.5 	Import	Native Support		• Check Playback
	Export	Final Production		Export to Final Cut Pro
Metafuse 	Import	Native Support		• Ecode
	Export	*Codec of Choice: DNxHD, XDCAM, ProRes		
Media Composer 5.5 6 	Import	Plug In 	• Metafuse • Cineform Remaster	• Check Playback • Edit
	Export	Final Production (deliverable file)		*Plug In allows you to import DPX files directly

CineForm

Neo 4K 3D Remaster 	Import	Native Support	• Encode
	Export	• CineForm 444 • ProRes 444 • (other installed Codecs)	*Once files are converted to CineForm 444, you can import them

Eyeon

Fusion 6 	Import	Native Support	• Edit
	Export	Final Production	

Maxon

Cinema 4D 	Import	Native Support	• Edit
	Export	Final Production	

NewTek

LightWave 3D 10.1 	Import	Native Support	• Check Playback
	Export	NLE / Final Production	• Apply Color Correction • Apply LUT • Edit

The Foundry

Nuke 6.3 Furnace 4.2 FurnaceCore 4.3 	Import	Native Support	• Check Playback
	Export	NLE / Final Production	• Apply Color Correction • Apply LUT • Edit

Sony

Vegas 	Import	Planned Support of Gemini DPX files (near future)	• Edit
	Export	Final Production	

Grass Valley

Edius 5 6 	Import	Native Support	• Create a new bin
	Export	Final Production	• Import File • Select 'File As Sequence'

Black Magic

DaVinci Resolve Resolve Lite 	Import	Native Support	• Check Playback • Apply Color Correction • Apply LUT • Edit
	Export	NLE / Final Production	
Media Express 	Import	Native Support	• Check Playback • Encode *If you have DeckLink 3D, or 4:4:4 card, it will playback and exp
	Export	Uncompressed Quicktime Movie	

AJA

DPX Translator 	Import	Native Support	• Check Playback • Encode
	Export	Uncompressed Quicktime Movie	

DPX Viewers

DJViwer 	Import	Native Support	• Check Playback
	Export	Jpeg, DPX, etc.	
XNView 			
POM DPX Head Editor 			
Photoshop			
Media Express			
DPX Translator			

APPENDIX

Firmware Updates

We strongly recommend you always keep your Gemini 4:4:4 updated with the latest firmware.
We frequently add new features and bug fixes at no cost.

Firmware Update Instructions

We recommend that you print out these instructions, if possible (p22-25).

1. Your computer must have an internet connection so you may access our website.
2. Navigate to our website: <http://www.convergent-design.com/FirmwareUpdates/Gemini444.aspx>

On the Right Side of the page, you will find “Current Firmware”.
Make a note of the firmware version that you will be downloading.

3. Format a SSD in the Gemini 4:4:4 (ensuring that no important clips are on the SSD first).
4. Insert the formatted SSD card in the transfer station.
5. Connect the transfer station to your computer, connecting both the USB and eSATA cables to your computer and the transfer station.

If your computer does not recognize the SSD, you may need to reboot your computer.

- a. We recommend creating a folder named something like the following:
Gemini 444 Firmware 2011-11-11-001 (1.0.105)
(Use today’s date and firmware number as listed in our webpage.) But you may create a folder using a folder name of your choice.
6. Navigate to Gemini 444 | [Firmware Updates](#).

On the Right Side of the page, you will find the Current Firmware and Release Notes.

7. Click on the firmware version that you wish to download.
Note: You may reinstall an earlier version of the firmware, if desired.

For Windows 7: (Other Windows Computers will be similar)
See below for Mac instructions

8. Click on Save As.
9. Navigate to the folder you just created.
10. Click on Save. The file you saved will be Gemini 1.0.105.zip
(but with the current firmware version number)
11. Navigate to this folder and file. (You may just click on "Open Folder")
12. Double Click on this file. It will be something like "Gemini 1.0.105.zip" but with the current firmware number.
13. Click on Extract All Files.
14. Click on Extract.
15. Double Click on Gemini 1.0.105 (or current firmware version number).
16. Drag and Drop the }GEM_UPDATE{ folder to your SSD Drive
(Listed under Computer) on the left hand side of your screen.

Note: The SSD may be "No Name", and it can be any Drive Letter", but it will have a }CLIPS{ folder on the drive.

Do not copy the firmware update into the }CLIPS{ folder.

Answer Yes to: "Do you want to copy this folder without Encryption?"

And Answer Yes to: "Do you want to copy this file without Encryption?"

Skip over "For Mac" instructions to finish the update.

For Mac

8. Start with Steps 1 through 8 above.
9. Double click on the }GEM_UPDATE{.zip
10. Copy or Drag }GEM_UPDATE{ folder to SSD.

For Both Mac and Windows (PC continued)

1. If done successfully, you will have:

}CLIPS{	(An Empty Folder)
}GEM_UPDATE{	(The Update Folder)
}GEMINI{.UPD	(The Actual Firmware Update File)
2. Use the “Safely Remove Hardware” option or shutdown/restart your computer gracefully, to ensure that the firmware has been completely transferred to the SSD.
3. Otherwise, the firmware update may not be successfully copied to the SSD, and then the Gemini 4:4:4 will not find the firmware update.
11. Ensure that you have adequate power to power the Gemini 4:4:4, either battery or AC Power. The firmware update takes less than 5 minutes, but please ensure that you have at least 30 minutes of battery time remaining to ensure safety.
12. Power up the Gemini 4:4:4.
13. Removing any video input cables.
14. Remove all SSD's.
15. Insert the SSD with the firmware update.
16. Then power on the unit.
17. You will see a Firmware Update screen if the file is on the SSD properly.
18. Follow the On-Screen Prompts to complete the firmware update.
19. When complete it will say: “DONE - PLEASE REMOVE UPDATE DRIVE”
(Please remove the SSD; The unit will then power off and back on automatically).
20. If you wish to then reuse this SSD (normally the case, unless you have additional Gemini 4:4:4's to update):

- a. Insert the SSD back into the Gemini 4:4:4
- b. Click on Cancel (to avoid performing the Firmware Update again)
- c. Reformat the SSD (Click on Menu, then Gemini, then SSD's, then Format SSD1 or Format SSD2)

This step is very important:

Then power off the Gemini 4:4:4, then Power it back on.

If you fail to perform this step to power cycle the unit, then all features of the Gemini 4:4:4 may not work properly.

TROUBLE SHOOTING: ! UPDATE FAILED ! or ! EMERGENCY UPDATE !

Check your power source, pull the power, and then run the update again. MAKE SURE THERE IS NO VIDEO SOURCE plugged into the unit, and that there is only ONE SSD PRESENT.

If this process fails twice, contact [Support](#).


Specifications

Feature	Specifications
Video Standards	HD-SDI, SMPTE 292M; HD-SDI Dual-Link, (SMPTE 372M; (HD-SDI 3G, SMPTE 424M - Planned)
Video Formats	1080p23.98/25; (1080p24/29.97/30/50/59.94/60, 2048x1080p23.98/24 - Planned)
Video I/O	Four BNCs, (2 Input, 2 output), (One HDMI (Type C) Output – Planned)
Record Features	Uncompressed RGB 10-Bit 4:4:4 Recording into DPX file format (audio recorded into WAV file)
	Spans across drives (for longer record times) or (Record simultaneously to both drives – Planned)
	(Video can be recorded with or without baked-in LUTs – Planned)
Metadata	Reel Number, Scene Number, Take Number, Shooting Day, Camera Number and Project Name
Playback Control	Selection of One or More files to Play, (Play, Pause, Fast-Forward, Rewind and Step – Planned)
S-Log, Log-C Support	Support for S-Log, (Log-C and user programmable 1D LUTs - Planned)
Media	Two Slots for 1.8" Solid State Drives (SSD), 256GB / 512GB sizes; Spanning Supported
	SSD Performance: 250 MBytes/Sec Write, 415 MBytes/Sec Read, 6 Gbps SATA Interface
	Note: Only SSD Media supplied by Convergent Design can be used in the Gemini
Transfer Station	1.8" SSD to 6 Gbps eSATA transfer station included
Built-In LCD Monitor	5" high brightness LCD, 800 cd/m², 800 x (RGB) x 480 Pixels, 24-Bit, 900:1 True Contrast, Wide 170° Viewing Angle, Color Calibrated at Factory
	1:1 Pixel Mode (User positioning of desired window via touch-screen control – Planned)
Software Compatibility	Support for Avid, Final Cut Pro with GlueTools, Premiere, Smoke, Flame, DaVinci, others
Menu System	Touch Sensitive menu system, Menus can be hidden, LCD can be dimmed
Timecode	HD-SDI Embedded (SMPTE RP-188) or LTC via optional cable or (Internal Timecode - Planned)
Digital Audio I/O	HD-SDI Embedded uncompressed, 24-Bit, 48K; 2-channels, stored in WAV format.
Analog Audio I/O	(3.5 mm jacks, mic or consumer line level input; headphone or consumer line level output planned)
3D - Dual Stream (Option)	(Paid option for Full Stereo (dual stream) record and playback in a single Gemini unit – Planned);
	Cameras must be Gen-locked to operate properly with the Gemini
	(Left and Right Video Streams recorded as individual files, in full uncompressed – Planned)
	(Vertical Flip, Horizontal Flop, for either/both streams – Planned)
	(Individual output of each stream or Combine: Side by Side, Line by Line, Anaglyph, 50/50 Composite and Luma Differencing – Planned)
ARRIRAW (Option)	Support for ARRIRAW recording and playback with Confidence Monitoring planned for March 2012
Remote Control (Option)	Wired Remote Control with Tally Light and LTC I/O (Options are extra cost items)
Power Requirements	5 to 19 Volts DC, 8 to 16 watts (active) / 4.0 watt (power-save mode planned); 7-second boot-up time
Size, Weight	138 x 120 x 37 mm (5.4 x 4.7 x 1.45"); 612g (1.35 lb); Milled Aluminum Case
Environmental	-10 to +40°C Ambient Temp (Operating) / -20 +70°C (Storage)
Gemini Production Kit	Gemini 4:4:4 Recorder, eSATA Transfer Station, HD-SDI cables, HDMI cable, Hot shoe with 1/4"x20 Ball Mount, Universal AC Power Supply, 4-Pin XLR Power Cable, D-Tap Power Cable, Stylus, Custom Fitted Hard Plastic Case
Optional Accessories	256GB / 512GB SSD Media, extra Transfer Stations, (DC to DC Converter (Input: 20 to 32V, Output: 12V), (Sun Shade, Remote Control – Planned)
Notes	1080p29.97/30 and 1080p50/59.94/60 data (planned) must be striped across both drives, so simultaneous recording / 3D is not supported for these formats. (Data from two SSDs can be readily combined for editing). Also 1080p50/59.94/60 (planned) only supported in 4:2:2 sampling.
	Specifications subject to change without notice.


Record Times - See Page 15.

Gemini Mechanical Drawings

Useful for your mounting needs and designs, please find below mechanical drawings of the Gemini 4:4:4.



Remote Connector Pinout



Firmware Version 1.0.592 (see also [Release Notes](#))

Features

- Added support for 1080p 24.00 frame rate (in addition to the already supported 1080p23.98 and 1080p25). Additionally, 1080p23.98 is reported more precisely as 23.98 in the Input Status window of the LCD screen.
- The DPX file naming convention was changed:
 - For the character preceding the frame counter digits, we replaced the “.” with a “_”
 - Files now begin at “0000000” instead of “0000001”, and count forward as before.

Example: For a clip named CLIP0000001, the DPX files will be named:

```
CLIP0000001_0000000.DPX
CLIP0000001_0000001.DPX
CLIP0000001_0000002.DPX ...etc.
```

- Fixed Outputs: Mode setting to be correctly saved when the setting is changed.
- Added a “Next Take” info button on the left side of screen, which when chosen displays the Clip, Scene, and Take which will be used for the next recording. (Please refer to the Metadata discussion below).
- Fixed bug in which timecode would inappropriately repeat or skip from one DPX file to the next within a recording.
- Fixed rare (0.000001%) pixel repetition within video frames.
- Lessened the sensitivity of scroll buttons when scrolling and adjusting values on the LCD screen.
- Added Support for CineFlex cameras with earlier firmware versions that do not comply with SMPTE Specs. Dual-link HD-SDI signals will now be recognized appropriately from these cameras.
- Added Metadata functionality:
 - Metadata may be entered and edited through the “Metadata” tab along the left side of LCD screen (in Live/Rec Mode).
 - The “Scene” and “Take” fields (along with the Clip Name) for the next recording are displayed just above the timecode display, which is located along the bottom row of the LCD screen, when the “Next Take” info button is selected (on the left bottom of LCD).
 - During Record, Metadata is saved in various locations within the header of every DPX file (the Metadata within the DPX header is viewable within some software programs on a computer), and additionally the Metadata is stored in a separate XML file (alongside the DPX files for a given recording).

- Also, the Metadata is stored, within the DPX header:
 - the “Reel”, “Scene”, “Take”, and “Day” values are placed in the “Slate Info” defined field in the DPX header
 - the “Reel” value is additionally placed in the “Input Device Name” field of the DPX header
 - the “Camera” value is placed in the “Input Device Serial Number” field of the DPX header
 - the “Project” value is placed in the “Project” field of the DPX header
- Most Metadata is displayed for each clip in the Play List (in “Play/Review” mode on the Gemini Recorder). This includes Scene, Take, Timecode, Date, Time, and Shooting Day.
- Added 2-channel audio support over SDI, recorded as WAV files (and placed alongside the DPX files for a given recording). WAV file will only be produced if audio is present over the incoming SDI stream during record.
- Added Play List / Play Selection functionality:
 - Clips may be selected for Playback out of the Gemini via the “Play List” tab along the left side of the LCD screen (in Play/Review mode).
 - All selected clips will be played in sequence, and optionally the playback will loop continuously (if the “Loop” option is selected), until manually stopped.
 - The default behavior of the Play List is to play and loop the last recorded clip.
- Added Screen Flip function (Gemini->Set->LCD->Flip) to flip the Video and On-Screen Display by 180 degrees. This is to allow more flexibility of mounting the Gemini 4:4:4, as it can now be mounted upside down, while still viewing the image and menus in the upright position. This does not flip the recorded image. Flipping of the recorded image will come with the 3D Option.
- Added LCD Screen / LED Brightness setting (Gemini->Set->LCD->Brightness) :
20% to 100% Brightness, adjustable in 10% increments.
- Added LTC timecode input source (via remote port and adaptor cable) (Inputs->Timecode->Source).
 - LTC Timecode may be used in conjunction with the Record->Trigger->Timecode setting to start and stop recordings on the Gemini (via incrementing Timecode for starting record, and stopped Timecode for stopping record), in the same manner as with Embedded SDI Timecode.
- Added current time/date display via the System Status button (lower left corner of LCD touch-screen, press button to bring up a larger System Status Info box).
- Beta support for 3G video inputs is included in this release.

Note** : Due to the addition of audio files, XML files, and Play List in this firmware release, any SSD to be used for recording with the new firmware will first require a fresh formatting within the Gemini Recorder (with the new firmware installed). Additionally, for any SSD's containing clips recorded on previous firmware, the Gemini Recorder will not provide a Play List for these clips – the only Play function will be “Play All”. In order to play clips recorded with earlier firmware, you must select the “All” function in the Play List, and

insert SSD's with the older clips only after powering the unit.

Please note that the Gemini 4:4:4 may be used to record from 4:2:2 sources in addition to 4:4:4 sources

Known Issues - 1.0.594

- During playback of clips from the Gemini Recorder: if the "Loop" option is selected, the video/audio can get out of sync with respect to each other over time. Additionally during "Loop" play, the audio may disappear altogether. These are only limitations of the "Loop" play; the actual recorded video/ audio files are intact and in sync.
- During playback of clips from the Gemini Recorder: the only functions available are "Play" and "Stop" (both functions are available via the Play/Stop button on the bottom of screen). At this time no other Play functions (such as Pause or Trick Play functions) are available.
- During playback: on rare occasions, the video can shift vertically. Restarting the Play will correct the video shift. This is only present while playing from the Gemini; the actual recorded video files are intact.
- HDMI Output and Analog Audio Input are not functioning at this time.
- Single-Link video inputs must be attached to the "SDI A In" port on the Gemini.
- When using Timecode Trigger as the Record Trigger, repeated timecodes may be experienced on the final 2 or 3 frames of a given recording.
- For the Metadata fields, no method exists to clear these fields back to default values.

Trouble Shooting & Support

Please read the User Manual before contacting support. We highly recommend that you follow these steps:

- (1) **UPDATE YOUR GEMINI:** Visit the Gemini 4:4:4 Firmware Updates page on the website and confirm that you are running the latest version. Please refer to 'Firmware Updates' on page 22 for more about checking the system for current version and updating.
<http://www.convergent-design.com/ProductUpdates/Gemini444.aspx>
- (2) **VISIT OUR FORUM:** We have a very active forum and you may find the answer you are looking for, as well as support from the Convergent Design community.
<http://www.dvinfo.net/forum/convergent-design-nanoflash/>
- (3) **REFER TO DOCUMENTATION:** Please read all of this User Manual, as well as our Gemini 4:4:4 FAQs which document basic usage and help answer common questions.
- (4) **CONTACT US:** If you still haven't found a solution to your support needs we are always happy to help you 24/7!


Support E-Mail: [cdsupport \(at\) convergent-design .com](mailto:cdsupport@convergent-design.com)

Sales E-Mail: [cdsales \(at\) convergent-design .com](mailto:cdsales@convergent-design.com)

Main Telephone: ++(720) 221-3861

Sales and After Hours Support Telephone: ++ (719) 930-1376, ++803-278-0941

Web Site: <http://www.convergent-design.com> & www.Gemini444.com



We appreciate your questions, comments, feedback! We ARE listening! To reach out to us, look for this link on our website, or visit
<http://www.convergent-design.com/ProductUpdates/WereListening.aspx>

Limited Warranty

Convergent Design warrants Gemini 4:4:4, and all included accessories, against defects in material and workmanship for a period of 2 years (for registered units), 1 year (for non-registered units), and 3 months (for units used as rentals) from the original date of purchase.

Convergent Design disclaims all other warranties.

Convergent Design will not be liable for damages of any kind, including, but not limited to, compensation or reimbursement on account of failure of the unit, or any of its accessories, or its recording media, external storage systems, or any other media or storage systems to record or playback content of any type. Also Convergent Design will not be liable for a failure of the unit to properly record or play back for any reason. Convergent Design's total liability, in all cases, is limited to the actual purchase price.

If you discover a defect, please refer to our Return Merchandise Policy below.

During the warranty period, Convergent Design, at its option, will repair or replace product or product components, which in its opinion prove defective, provided the unit is returned, freight charges prepaid, to Convergent Design. Parts and components used in the repair process may be recycled or repaired, at Convergent Design's sole discretion. This warranty service will be performed at no charge to the registered owner, provided the product is shipped prepaid to Convergent Design.

Convergent Design reserves the right to determine whether a needed repair is subject to the warranty as per its provisions stated herein. Transit damage caused by inadequate packing violates the warranty. The warranty will be void if, in the opinion of Convergent Design, the product has been damaged through accident, misuse, misapplication, or as a result of service or modification not authorized in writing by Convergent Design.

Opening the unit and breaking the warranty seals, voids the warranty, unless specifically authorized in advance by Convergent Design.

WARNING: THE FOLLOWING ARE NOT COVERED UNDER WARRANTY, AND ARE ITEMS FOR WHICH CONVERGENT DESIGN DOES NOT ACCEPT ANY RESPONSIBILITY:

- Damage due to the use of an AC power supply, other than the one supplied, or use of any inappropriate power source.
- Damage due to overheating conditions. The unit will attempt to shut down, if powered on, in the event of overheating, before damage can occur.

- Damage due to exposure to water, or other liquids, or excessive dust or sand.
- Damage caused by dropping or other rough handling.
- Damage caused by any overvoltage conditions or reverse voltage conditions.
- Any physical damage to the LCD and/or Touch Screen including scratches.
- Damage to any connector by using excessive force or rough handling.
- Any loss or corruption of video or audio data recorded on the unit, or any loss or corruption of data which is in any way associated with the Gemini 4:4:4.

Obtaining an RMA

It is our policy that all material and repair returns, whether in warranty or not, are only accepted if an RMA (Return Merchandise Authorization) Number has been issued for the products being returned.

E-mail Convergent Design at cdsupport (at) convergent-design .com to obtain an RMA number for a faulty unit, or call ++720-221-3861 (7:30 am to 5 pm Colorado, USA time).

Items must be returned within 15 days of receiving your RMA number.

Returned product must be securely packaged and must have the RMA number clearly marked on the outside of the package.

RMA numbers and return address may be obtained from Technical Support.

Convergent Design RMA # _____

4465 Northpark Drive, #400

Colorado Springs, CO 80907

EMAIL: cdsupport@convergent-design.com

WEBSITE: www.convergent-design.com or www.gemini444.com

Phone ++(720) 221-3861 (Preferred, Denver Time) or

++(866) 654-0080 or

++(803) 278-0941 (For After Hours Support 24/7)

++(719) 930-1376 (For After Hours Support 24/7)

Transit damage caused by inadequate packaging also invalidates the warranty agreement.

Please ship the unit in its original packaging, if possible.

Within the United States, the unit may be shipped directly to Convergent Design once an RMA is obtained.

Outside the United States, please coordinate with your dealer, which will then coordinate with our distributor for your part of the world. Our goal is to ensure that the units are shipped properly and that the units will clear customs without incurring extra charges. In some cases your local dealer or distributor may be able to provide you with a loaner unit.

All products must be shipped prepaid to Convergent Design, or preferably through the dealer from which the unit was purchased (if outside the US). If you purchased the unit from a dealer outside of your normal trading zone, then you may be charged for return shipping to your location.

For insurance reasons, Convergent Design cannot accept any product that is returned via U.S. Postal Service. Returns will be accepted from Federal Express, UPS, DHL, or other comparable freight carrier.

Products repaired out-of-warranty are shipped at customer's expense.